

# NONEL<sup>®</sup> EZ TL<sup>™</sup>

Nonelectric Trunkline Delay Detonators



## Product Description

**Nonelectric Trunkline Delay Detonators EZ TL** units consist of a length of yellow shock tube, with a surface detonator attached to one end and the other end sealed. The detonator is housed in a plastic EZ Connector block which facilitates easy connection to shock tube. A white J-hook is affixed near the sealed end. Easy-to-read, color-coded delay tags display the delay number and nominal firing time prominently. NONEL EZ TL detonators are designed for use with NONEL MS and NONEL EZ DET units to provide effective and accurate surface timing between blastholes and/or rows of blastholes in surface and underground blasting designs.



## Technical Information

### Properties

**Net Explosive Content per 100 units**  
(Excluding Shock Tube)

0.0240 kg  
0.0529 lbs

Net Explosive Content per 100,000 m shock tube

0.1043kg  
0.2299 lbs

#### Hazardous Shipping Description

Detonator assemblies nonelectric,  
1.4B, UN 0361 PG II  
1.1B, UN 0360 PG II



Delay Time (msec)	Connector Block Color
17	Yellow
25	Red
42	White
67	Black
100	Black

I-29-01-25-08  
See Product Disclaimer on next page.



TENAGA KIMIA SDN BHD (26191 A)

*Your Partner with*  
**TOTAL BLASTING SOLUTION**

# NONEL® EZ TL™

## Nonelectric Blast Initiation System

### Application Recommendations

**ALWAYS** be sure that the shock tube(s) are securely inserted, one at a time, into the plastic EZ connector. The head of the connector block should rise to accept the tube, and return to a closed position with an audible click.

**ALWAYS** ensure that the individual shock tubes remain aligned side by side in the EZ connector channel and do not cross over one another during insertion.

**ALWAYS** protect the plastic EZ connector and all shock tube leads from impact or damage. Use care when placing blasting mats and cover material on top of the blasting circuit. The EZ connector contains a detonator and is subject to detonation caused by abuse such as impact. Shock tube which has been cut, ruptured or damaged may cause misfires.

**NEVER** use NONEL EZTL detonators with detonating cord. The low strength surface detonator will not initiate detonating cord.

**NEVER** attempt to disassemble the delay detonator from the EZ connector block or use the detonator without the connector.

**NEVER** place more than 6 shock tube leads into an EZ connector block. Misfires may result.

### Transportation, Storage and Handling

NONEL EZTL must be transported, stored, handled and used in conformity with all federal, state, provincial and local laws and regulations.

For maximum shelf life (2 years), NONEL EZTL must be stored in a cool, dry, well ventilated magazine. Explosive inventory should be rotated. Avoid using new materials before the old. For recommended good practices in transporting, storing, handling and using this product, see the booklet "Prevention of Accidents in the Use of Explosive Materials" packed inside each case and the Safety Library Publications of the Institute of Makers of Explosives.



## Technical Information

### Packaging

Length		Case Type		Quantity/ Case	
m	ft	1.4B	1.1B	1.4B	1.1B
6	20	S	L	50	180
7	24	S	L	40	150
9	30	S	L	40	150
10	34	S	L	30	120
12	40	S	L	30	120
15	50	S	L	30	100
18	60	S	L	25	100
21	70	L	L	90	90
24	80	L	L	90	90
30	100	L	L	75	75
36	120	L	L	75	75

- Length rounded to nearest one-half meter.
- Case weight varies by length & delay; see case label for exact weight.

### Case Dimensions

**S** - 460 x 230 x 255 mm

**L** - 640 x 320 x 430 mm

**Product Disclaimer** Tenaga Kimia Sdn Bhd, its subsidiaries and distributors disclaim any warranties with respect to this product, the safety or suitability thereof, or the results to be obtained, whether express or implied, INCLUDING WITHOUT LIMITATION, ANY IMPLIED WARRANTY OF MERCHANTABILITY OR FITNESS FOR A PARTICULAR PURPOSE AND/OR OTHER WARRANTY. Buyers and users assume all risk, responsibility and liability whatsoever from any and all injuries (including death), losses, or damages to persons or property arising from the use of this product. Under no circumstances shall TKSB, subsidiaries and distributors be liable for special, consequential or incidental damages or for anticipated loss of profits.



## TENAGA KIMIA SDN BHD (26191-A)

No. 8, Jalan SS 22/21, Damansara Jaya, 47400 Petaling Jaya, Selangor Darul Ehsan, Malaysia.

OR P.O. Box 11674, 50754 Kuala Lumpur. Tel: 03-7729 7464 Fax: 03-7729 8383

Email: [tkb@tenagakimia.com](mailto:tkb@tenagakimia.com) Website: [www.tenagakimia.com](http://www.tenagakimia.com)