

NONEL® Starter

Application Recommendations

ALWAYS trim excess lengths of detonating cord from bunch block. Detonating cord tails lying across outgoing trunkline can interfere with normal function.

ALWAYS use NONEL Lead Line to splice onto the NONEL Starter unit to make up a custom length nonelectric starter assembly whenever the length of NONEL Starter unit is not sufficient to position the blaster safely.

ALWAYS use the plastic connector sleeves packaged in each NONEL Lead Line case to make a reliable splice connection to NONEL Starter unit.

ALWAYS hook the NONEL Starter bunch block to the blast round after all equipment and non-essential personnel are clear of the blast area.

ALWAYS unspool NONEL Starter unit by hand if the bunch block has been attached to the blast round.

ALWAYS place the bunch block so the lid is face down and cover the bunch block with drill cuttings or other inert material to help prevent shrapnel cut-off after attaching the bunch block to detonating cord or shock tube.

ALWAYS replace the NONEL Starter if it is damaged.

When using NONEL Starter detonators with a detonating cord trunkline, **ALWAYS** place the detonating cord in the bunch block parallel to the detonator with the detonator pointing in the desired direction of initiation.

NEVER attempt to initiate more than eight (8) NONEL shock tubes or one (1) detonating cord trunkline with the bunch block. Misfires may result.

NEVER place detonating cord and shock tube in the same NONEL Starter bunch block. Misfires may result.

NEVER attach the NONEL Starter bunch block to the blast round until after the NONEL Starter shock tube deployment is complete whenever a NONEL Starter unit is to be unspooled by any method other than by hand.

NEVER run over NONEL Starter detonators with equipment. This may damage the shock tube and may cause a misfire.

Transportation, Storage and Handling

NONEL Starter must be transported, stored, handled and used in conformity with all federal, state, provincial and local laws and regulations.

For maximum shelf life (2 years), NONEL Starter must be stored in a cool, dry, well ventilated magazine. Explosive inventory should be rotated. Avoid using new materials before the old. For recommended good practices in transporting, storing, handling and using this product, see the booklet "Prevention of Accidents in the Use of Explosive Materials" packed inside each case and the Safety Library Publications of the Institute of Makers of Explosives.



Technical Information

Packaging

Length		Case Type	Coil Type	Spools/ Case
m	ft	1.4B		1.4B
150	492	L	Detpak	3
300	984	L	Detpak	3
500	1640	S	Detpak	1
750	2460	S	Detpak	1

- Length rounded to nearest one-half meter.
- See case label for exact case weight.

Case Dimensions

S - 700 x 350 x 200 mm
L - 400 x 400 x 250 mm

Product Disclaimer Tenaga Kimia Sdn Bhd, its subsidiaries and distributors disclaim any warranties with respect to this product, the safety or suitability thereof, or the results to be obtained, whether express or implied, INCLUDING WITHOUT LIMITATION, ANY IMPLIED WARRANTY OF MERCHANTABILITY OR FITNESS FOR A PARTICULAR PURPOSE AND/OR OTHER WARRANTY. Buyers and users assume all risk, responsibility and liability whatsoever from any and all injuries (including death), losses, or damages to persons or property arising from the use of this product. Under no circumstances shall TKSB, subsidiaries and distributors be liable for special, consequential or incidental damages or for anticipated loss of profits.



TENAGA KIMIA SDN BHD (26191-A)

No. 8, Jalan SS 22/21, Damansara Jaya, 47400 Petaling Jaya, Selangor Darul Ehsan, Malaysia.
 OR P.O. Box 11674, 50754 Kuala Lumpur. Tel: 03-7729 7464 Fax: 03-7729 8383
 Email: tkb@tenagakimia.com Website: www.tenagakimia.com